

BRK®**SM6W01**

✓ **LED INDICATORS
SIMPLIFY
MAINTENANCE
& REPLACEMENT**

✓ **AA BATTERY BACKUP**

✓ **SIDE-LOAD BATTERY
DRAWER**



CAT. SM6W01, SM6W01-CP, SM6W01-P48, SM6W01-P48NB

SMOKE ALARM

HARDWIRED SMOKE ALARM WITH REPLACEABLE BATTERY BACKUP

LED ALARM INDICATORS

Low battery and end-of-life warnings with light signals to provide advanced warning and efficient diagnostics

SOFTCUE™ REPLACEMENT REMINDERS

Reduce disruptive alarm chirps

TRIM RING

Simplifies replacement installs (optional)

INTERCONNECT

When one sounds, all compatible alarms sound. Works with most hardwired First Alert® and BRK alarms.*



ARCHITECTURAL AND ENGINEERING SPECS

The smoke alarm is a BRK Model SM6W01 and provides at minimum the following features and functions:

1. Photoelectric smoke-sensing with a 10-year service life
2. Powered by 120V AC, 60Hz
3. Replaceable AA batteries. Replace with Kendal LR6, Energizer E91, or Duracell MN1500.
4. A solid-state piezo horn rated at 85 dB at 10 feet
5. The unit shall have a plug-in connector and be capable of interconnection with up to 18 alarms, 12 of which can be smoke alarms
6. The unit shall have an "end of life" signal (five chirps) and be capable of temporary silencing for up to two days, after which the signal will resume. After about two weeks, the signal cannot be silenced.
7. Visual Power LED indicator to confirm the unit is receiving power
8. Latching feature easily identifies the initiating alarm after condition has been addressed
9. Silence feature—temporarily silence unwanted nuisance alarms
10. The unit shall perform self-diagnostic tests and issue a malfunction warning (three chirps) if the unit malfunctions
11. Two locking features—tamper resistant locking pins that lock the battery drawer and/or alarm to the mounting bracket
12. The unit shall be capable of operating between 40°F (4.4°C) and 100°F (38°C) and relative humidity between 10% and 95%
13. Interconnect with First Alert smart alarm (SC5) to enable app alerts and remote monitoring so you're notified when a hazard is detected
14. The test button should check all alarm functions by stimulating the chamber to simulate a smoke condition, causing the unit to alarm.
15. The unit shall have a gasketless base for easy installation and be capable of keeping alarm secure over a wide rotation range to allow for true alarm alignment
16. A fully screened sensing chamber resists entry of dust and small insects thereby helping reduce the probability of unwanted alarms
17. The unit shall at a minimum meet the requirements of UL217, CSFM, NFPA 72, NFPA 101, and the ICC

INSTALLATION OF ALARM

Installation of this smoke alarm must conform to NFPA 72. Always check your local building codes. Follow all instructions for placement as outlined in the user's manual in sections titled "Recommended Locations for Smoke Alarms" and "Locations to Avoid for Smoke Alarms."

TECHNICAL SPECS

Alarm Dimensions:	5.2" Dia. x 1.76" H
Weight:	0.54 lb
Battery:	AA
Operating Voltage:	120V AC @ 60Hz, 0.7A
Temperature Range:	40° – 100°F (4.4° – 38°C)
Humidity Range:	20% – 95% RH (Agency Compliance – 93% max.) non-condensing
Audio Alarm:	Meets or exceeds current UL standards of 85 dB at 10 feet (3 meters)
Test/Silence:	Push and release center button to test and silence alarm
Interconnections:	Yes
Indicator Lights/Sounds:	
Smoke Alarm LED:	2 seconds on, 2 seconds off—smoke latch 3 beeps with red flashes—smoke alarm
Power LED:	Constant green—AC power
Battery LED:	1 beep with yellow flash—low battery 6 soft beeps with yellow flash—pre-warning
Replace Device LED:	2 yellow flashes per minute—clean device 3 beeps with yellow flashes—malfunction 5 beeps with yellow flashes—end of life 6 soft beeps with yellow flash—pre-warning

* Up to 12 smoke alarms and 6 other alarms. Refer to product manual for compatible alarms.

resideo
www.resideo.com

BRK | **FIRST ALERT**

© 2026 Resideo Technologies, Inc. All rights reserved. These products are manufactured by Resideo Technologies, Inc. and its affiliates.

brkelectronics.com